

SEW-EURODRIVE MC07B0004-5A3-4-00

MC07B0004-5A3-4-00 | SEW | MOVITRAC® B Frequency Inverter

Manufacturer : SEW

Part Number : MC07B0004-5A3-4-00

MOVITRAC® B Frequency Inverter

Power supply connection : 400 V, 3-phase

Motor power : 0.37 kW / 0.50 HP

Rated output current : AC 1.6 A

Size : 0XS

Weight : 1.3 kg / 2.9 lb

Compact frequency inverter for space-saving installation

Its straightforward operation saves time during startup

Broad voltage and power range

3x AC 380 - 500 V: 0.25 kW - 90 kW

3x AC 230 - 240 V: 1.5 kW - 30 kW

1x AC 230 - 240 V: 0.25 kW - 2.2 kW

Overload

125 % IN continuous duty

150 % IN for at least 60 s

Safe Torque Off (STO) EN ISO 13849-1 PL d (as standard from 5.5 kW)

Adapted to your application

The design enables the integration of

Fieldbus interfaces

Functional safety technology options

Input/output extensions

AC DRIVE

INVERTER

MOVITRAC B

0.37 KW (0.50 HP)

You can contact us through the following contact information

www.sparetechplc.com +86 180 3000 5825 sales@sparetechplc.com

380-500 VAC SUPPLY
50/60 HZ
SUPPRESSION C2
3 PHASE
4Q WITH BRAKE CHOPPER
STANDARD



You can contact us through the following contact information

www.sparetechplc.com +86 180 3000 5825 sales@sparetechplc.com