

Schneider Electric BMXXBE1000

Model: BMXXBE1000

Brand: Schneider Electric

Series: Modicon X80

Modicon X80 Rack Expansion Module (X-bus)

—— Hardware ——

Type: X-bus expansion module

Function: X-bus connection between multiple racks

Installation: Right-end XBE slot (does not occupy slots 00-11)

Connectors: 2 × 9-pin SUB-D (X-bus in/out)

Indicators: RUN, COL, rack address LEDs (0-3)

—— Environmental ——

Operating temperature: 0° C to +60° C

Storage temperature: -25° C to +70° C

Relative humidity: 5% to 95% (non-condensing)

Protection rating: IP20

—— Physical ——

Dimensions (H × W × D): 100 × 28 × 93 mm

Weight: 0.10 kg

Slot occupation: 1 (XBE slot)

—— Lifecycle ——

Lifecycle: Active (shared I/O platform for M340 and M580) (Last verified: 2026-09)

You can contact us through the following contact information

www.sparetechplc.com +86 180 3000 5825 sales@sparetechplc.com